



79	W-21454	1	MEGOMM
80	W-25572	.0005	MFD
81		.0005	MFD
82	W-21454	1	MEGOMM

Model 146 (1932)

	1 AF	2 AF	RECT
	○	○	○
1 IF	89	46	82
○			
58	OSC-1 DET		
	○		
2 IF-2 DET	57		
○	RF		
58	○		
	58		
A.V.C		2 AF	
		○	
	56	46	

FRONT

Line voltage 117½ volts (235 for 220
volt receivers)

Models 146 and 146-1 are nine tube super-heterodynes for operation from A. C. electric circuits. Model 146 uses a single speaker

MODEL 146
Schematic
Voltage

-58	R. F. Amplifier	195	62	0	2.5*	2.5
-57	Osc. Detector	195	132	0	9.0	2.5
-56	1st I. F. Amplifier	200	62	0	2.0*	2.5
-58	2nd I. F. Amp. and Diode	0	105	200	5.0	2.5
-56	A. V. C.	60			70.0	2.5
-89	A. F. Amplifier	180	200	0	20.0	6.0
-46	Class B Output	350			0	2.5
-46	Class B Output	350			0	2.5
-82	Rectifier	380			0	2.5

* Measured across cathode resistors